


## 21. SERVICE MENU SETTINGS













In order to reach service menu, First Press “**MENU**” Then press the remote control code two times, which is “**4725**”.


In first screen following items can be seen:



## 21.1. Video Settings

### VIDEO SETTINGS


RF AGC SECAM		3
RF AGC NEIGHBOUR NO IMAGE NO		3
RF AGC NEIGHBOUR NO IMAGE YES		3
RF AGC NEIGHBOUR YES IMAGE NO		6
RF AGC NEIGHBOUR YES IMAGE YES		6
RF AGC TEST		3
ADC Calibration Source	EXT-1	
ADC Calibration R Gain		82
ADC Calibration G Gain		82
ADC Calibration B Gain		81
ADC Calibration R Offset		0
ADC Calibration G Offset		0
ADC Calibration B Offset		0

 Change Value

 Back

 Exit

## 21.2. Audio Settings



## 21.3. Options

### Options-1

**OPTIONS 1**




Auto TV OFF	4 h
Power Up Mode	Last State
BacklightTrick Mode	Yes
Cable Support	No
EPG Type	2
Hotel Mode	Yes
LCN	No
PC Standby	Yes
Stby Search	Yes
Test Tool	Yes
Local Key	KeyPad
Volume Level	15

Read-only      Back      Exit


Options-2

## OPTIONS 2

Aps Sorting	Enabled
Dynamic Menu	Disabled
EPG Menus	Enabled
Transparent Text	Enabled
HDMI Number	2
HDMI Auto Switch	Enabled
Rc Type	Rc3900
DCF ID	4851.dcf
Touchpad Sw Version	0

 Read-only       Back       Exit

## 21.4. Tuning Settings



## 21.5. Source Settings

### SOURCE SETTINGS

SCART	Yes
SCART2	No
SCART2-S	No
SIDE AV	Yes
SCART-S	Yes
HDMI1	Yes
HDMI2	Yes
HDMI3	No
HDMI4	No
YPbPr	Yes
VGA/PC	Yes
BluRay	No

 Read-only

 Back

 Exit

## 21.6. Diagnostic

The screenshot displays a blue background with a black header bar containing the word "DIAGNOSTIC" in white. Below the header, a list of diagnostic tests is shown on the left, and their corresponding results are shown in grey boxes on the right. The "Remote control test" result box is highlighted with a white border. At the bottom of the screen, there is a dark blue bar with the text "Press any key to test" on the left, and two buttons labeled "RETURN Back" and "MENU Exit" on the right.

Test Name	Result
Remote control test	OK
UHF test	OK
VHF test	OK
Factory reset	OK
Tuner I2C	OK
IF I2C	OK
HDMI I2C	NOK
Ethernet	NOK
EDID status	NOK
HDCP status	NOK
DDR Settings	NOK
CI+ credentials	NOK
MAC address	ff:ff:ff:ff:ff:ff

Press any key to test      **RETURN** Back      **MENU** Exit

## 21.7. USB Operations

USB operations option can not be used directly. It can be used for updating panel tool, hw configuration etc.



## **22. SOFTWARE UPDATE**

In MB62 project there is only one software. From following steps software update procedure can be seen:

1. MB62\_en.bin, mboot.bin and usb\_auto\_update\_T4.txt documents should copy directly inside of a flash memory(not in a folder).
2. Put flash memory to the tv when tv is powered off.
3. Power on the and wait when the tv is opened.
4. If First Time Installition screen comes, it means software update procedure is succesful.