

ADJUSTMENT INSTRUCTION WITH DEFAULT FACTORY DATA

1. SVC mode data Adjustment

NOTE!! When the EEPROM has been replaced, the SVC data should be restored as the function of individual system and specification.

[Enter and exit SVC mode]

Note: into the SVC mode, Initialize with default data.

- 1) Press 5 Seconds MENU buttons on both TV set and Remote Controller at the same time to get into SVC mode.
- 2) Press the Yellow button several times to find SVC Data.
- 3) Input the corresponding SVC data referring to Table below with the Volume Up/down key.
- 4) Press the OK button to memorize the data.
- 5) Press TV/AV button to exit SVC mode

2-1. Factory outgoing setting & Initialize with default data (into the SVC mode).

PAGE	ITEM	Factory outgoing setting	Initialize with default data	Ex	REMARK
DATA 1	AGC	15	15		Variable Data(0-31)
	RD	127	127		PC Contrast Coefficient-RED(0-255)
	GD	127	127		PC Contrast Coefficient-GREEN(0-255)
	BD	127	127		PC Contrast Coefficient-BLUE(0-255)
	RO	79	79		PC Brightness Coefficient-RED(0-63)
	GO	79	79		PC Brightness Coefficient-GREEN(0-63)
	BO	79	79		PC Brightness Coefficient-BLUE(0-63)
	PC CP	5	5		PC Charge Pump(0-7)
	50 PR *				* means current program NO.
DATA 2	FP	52	52		FM Prescaler(0-127)
	NP	122	122		NICAM Prescaler(0-127)
	SP	63	63		SCART Prescaler(0-127)
	S1 VOL	44	44		SCART1 Volume(0-127)
	S2 VOL	44	44		SCART2 Volume(0-127)
	50 PR *				* means current program NO.
DATA 3	200PR	0	0	0	100PR
				1	200PR
	TEXT	1	1	0	Not apply to TEXT
				1	Apply to TEXT
	TOP	1	1	0	TELETEXT TOP OFF
				1	TELETEXT TOP ON
	SCART	1	1	0	Apply to COMPONENT
				1	Apply to SCART
	ACMS	1	1	0	Not apply to ACMS
				1	Apply to ACMS
	CH+AU	0	0	0	Used except for CHINESS or AUSTRALIA
				1	Used CHINESS or AUSTRALIA
	SYS	1	1	0	BG//DK
1				BG//DK/L	
2				BG//DK/M	
3				RESERVED	
50 PR *					* means current program NO.
106	Opt 1				Translate HEX into DEC(DATA3VALUE1)

ADJUSTMENT INSTRUCTION WITH DEFAULT FACTORY DATA

2-2.SVC Data Table

PAGE	ITEM	Factory outgoing setting	Initialize with default data	Ex	REMARK	
DATA 4	DUAL	0	0	0	Not apply to DUAL option	
				1	Apply to DUAL option	
	MONO	0	0	0	Not apply to MONO option	
				1	Apply to MONO option	
	A2 ST	1	1	0	Not apply to NICAM STEREO option	
				1	Apply to NICAM STEREO option	
	VOL	1	1	0	Sound curve option 1	
				1	Sound curve option 2	
	LANG	4	1	0	ENG ONLY	ENGLISH ONLY
				1	EU-5EA	ENGLISH/GERMAN/FRANCE/ITALY/SPAIN
				2	EU CIS	EU-5EA + CIS
				3	ENG TURKY	ENGLISH + TURKY
				4	EU-12EA	English, German, FRANCE/ITALY/SPAIN, Netherland, Sweden, Norway, Denmark, Finlandi, Portugal, Rumania
				5	N EU 12EA	English , Netherland, Sweden, Norway, Denmark, Finland, Portugal, Rumania, Israel, Hungary, Czech, Russian
				6	YAHOO	YAHOO
				7	EU-6EA	ENGLISH / GERMAN / FRANCE / ITALY/SPAIN / Netherland
				8	KOREA	ENGLISH / KOREA
				9	JAPAN	ONLY SELECT JAPAN
				10	USA	ENGLISH/FRANCE/SPAIN
				11	S-AMERICA	ENGLISH / FRANCE / SPAIN / Netherland
				12	NTSC ENG	ENGLISH
				13	RESERVED	
				14	RESERVED	
	15	RESERVED				
	T-LAN	0	0	0	WEST EU	WESTEU/U.K/GERMAN/FRANCE/ITALY/ SPAIN/SWEDEN/CZECH Rep./NORWAY etc
				1	EAST EU1	POLAND/SLOVENIA/ROMANIA etc
				2	TURKEY EU	TURKEY
				3	EAST EU2	HUNGARY/SERVIA
				4	CYRILLIC1	ESTONIA
				5	CYRILLIC2	ESTONIA
				6	CYRILLIC3	RUSIA/UKRAINE/ESTONIA/CROATIA/KAZAKH STAN
				7	TURK GRE1	
				8	TURK GRE2	
				9	TURK GRE3	TURKEY/GREECE
				10	ARAB ERA	
11				ARAB ENG	ARAB CULTURE	
12				ARAB HEB1		
13				ARAB HEB2	ARAB/HEBREW	
14				FARS ENG	PARSI	
15	FARS FRA					
	50 PR *				* means current program NO.	
	57	Opt 2			Translate HEX into DEC(DATA4)	

ADJUSTMENT INSTRUCTION WITH DEFAULT FACTORY DATA

2-3. SVC Data Table

PAGE	ITEM	Factory outgoing setting	Initialize with default data	Ex		REMARK
DATA 5	FVS	1	1			Frequency voltage Disable/Enable(0-1)
	DVI	1	1			Fix (All Model application)
	D-TV	0	0			D-TV Disable/Enable (0-1)
	VCHIP	0	0			Violence Disable/Enable (0-1)
	WOFER	1	1			Fix (All Model application)
	PANEL	6	0	0	LG-30	Used LG-30 PANEL
				1	LG-23 A2	Used LG-23 A2 PANEL
				2	LG-23 B2	Used LG-23 B2 PANEL
				3	CMO-30 1	-
				4	CMO-30 2	Used CMO-30 PANEL
				5	LG A3P5 - 30	Used LG A3P5 -30 PANEL
				6	SS-32	Used SS-32 PANEL
				7	RESERVED	
				8	RESERVED	
				9	RESERVED	
				10	RESERVED	
				11	RESERVED	
				12	RESERVED	
				13	RESERVED	
				14	RESERVED	
	15	RESERVED				
	RESET	15	15	0	NEC-A	Save NEC-A TV Channel
				1	Marantz	Save Marantz TV Channel
				2	L-Model	Save L-Model TV Channel
				3	E-Model	Save E-Model TV Channel
4				M-Model	Save M-Model TV Channel	
5				KOREA	Save KOREA TV Channel	
6				USA	Save USA TV Channel	
7				RESERVED		
8				RESERVED		
9				RESERVED		
10				RESERVED		
11				RESERVED		
12				RESERVED		
13				RESERVED		
14				RESERVED		
15	RESERVED					
RGBsw	1	0	0	TDA8601	Used 32GTP	
			1	TEA5114	Used 32GLP (HLT-3220)	